

| CFL Lamps | | | | | | | | | | |
|--------------|-----------|----------------------------|---------------|-----------------------|------------------|----------------|-----------------------|-----------------------|--------------|---|
| Manufacturer | Model | Power | Compatibility | Number of CFL Lamps * | Dimming curve ** | Dimming mode** | Low dimming limit *** | High dimming limit*** | Observations | |
| E27 | HEITRONIC | 19519 | 25W | Yes | 1 | CFL 2 | Trail | 20% | 100% | |
| | IKEA | SPARSAM | 20W | Yes | 1-12 | CFL 2 | Trail | 18% | 100% | |
| | | TORNADO | 15W | Yes | 1-2 | CFL 2 | Lead | 1% | 100% | |
| | PHILIPS | PL-ELECTRONIC DIMMABLE | 20W | Yes | 1-4 | CFL 2 | Trail | 1% | 100% | |
| | | SOFTONE | 12W | Yes | 1-3 | CFL 2 | Trail | 8% | 100% | |
| | GOVENA | DIMM | 20W | Yes | 1 | CFL 1 | Trail | 1% | 100% | |
| | OSRAM | DULUX INTELLIGENT DIMMABLE | 18W | Yes | 1-3 | CFL 2 | Lead | 12% | 100% | For different dimming curve/mode of recommended ones flickering effects could appear at 100%. |
| | MEGAMAN | MM42102 | 11W | Yes | 1-3 | CFL 2 | Trail | 14% | 100% | Flickering during shutdown. |
| | | MM46012 | 11W | Yes | 1-3 | CFL 1 or CFL 2 | Trail | 6% | 100% | |
| WL218D | | 18W | Yes | 1-9 | CFL 2 | Trail | 11% | 100% | | |
| GU10 | MEGAMAN | BR1411D | 11W | Yes | 1-3 | CFL 2 | Trail | 5% | 100% | |

| LED Lamps | | | | | | | | | | |
|----------------|------------|--------------------------------|---------------|-----------------------|------------------|------------------------|-----------------------|-----------------------|--------------|--|
| Manufacturer | Model | Power | Compatibility | Number of CFL Lamps * | Dimming curve ** | Dimming mode** | Low dimming limit *** | High dimming limit*** | Observations | |
| E27 | OSRAM | PARATHOM CLASSIC A 60 ADVANCED | 12W | Yes | 1-10 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | PARATHOM CL A 60 | 12W | Yes | 1 | LED 1 or LED 2 | Lead/Trail | 2% | 100% | |
| | PHILIPS | MASTER LEDBULB MC DimTone | 8W | Yes | 1-8 | LED 2 | Trail | 26% | 100% | |
| | | MASTER LEDbulb MV | 17W | Yes | 1-3 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | LEDspot PAR 20 | 7W | Yes | 1-2 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | MASTER LEDbulb MV | 12W | Yes | 1 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | MASTER LEDspot PAR 38 MV | 18W | Yes | 1-4 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | MASTER LEDspot PAR 30s MV | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 2% | 100% | |
| | MEGAMAN | LED GLOBE LG0708dv2 | 8W | Yes | 1-3 | LED 2 | Lead/Trail | 1% | 100% | |
| | | LED CLASSIC LG0408dv2 | 8W | Yes | 1-3 | LED 2 | Lead/Trail | 1% | 100% | |
| | VERBATIM | LG1907dv2 | 7W | Yes | 1-10 | Lineal, LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | Classic A | 9W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | LEDA | PAR38 | 18W | Yes | 1-12 | LED 2 | Trail | 10% | 95% | It is not possible to dim more than 5 lamps per channel. |
| | CALEX | ? | 7W | Yes | 1 | Lineal, LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| GU10 | OSRAM | PARATHOM PRO PAR16 35 ADVANCED | 8W | Yes | 1-3 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | PARATHOM PRO PAR16 35 ADVANCED | 9W | Yes | 1-3 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | PARATHOM PRO PAR16 50 36° | 7,5W | Yes | 1-8 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | BGENOSTORE | ONLINE MR 16 | 9W | Yes | 1-5 | Lineal, LED 1 or LED 2 | Trail | 1% | 60% | |
| | RENOVABLES | LEDspot GU10 MV DIMMABLE | 5W | Yes | 1-6 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | PHILIPS | MASTER LEDspot MV | 7W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | MASTER LEDspot MV | 4W | Yes | 1 | Lineal, LED 1 or LED 2 | Trail | 1% | 100% | |
| | | MASTER LEDspot MV | 5,5W | Yes | 1-4 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | | MASTER LEDspot MV D 4-35 28mA | 4W | Yes | 1-6 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | MASTER LEDspot MV D 4-35 29mA | 4W | Yes | 1-14 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | BRICOLUX | | 3W | Yes | 1-3 | Lineal, LED 1 or LED 2 | Trail | 1% | 100% | |
| | CALEX | | 6W | Yes | 1 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | MEGAMAN | LR1108d-50H35D | 8W | Yes | 1-2 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| | InteWatt | 01-SLAGU10DNW | 5W | Yes | 1-2 | LED 1 or LED 2 | Lead/Trail | 1% | 100% | |
| CONECTOR LIBRE | FOKE | Barra LED (336 LEDs) | 22W | Yes | 1 | Lineal, LED 1 or LED 2 | Trail | 1% | 100% | |

| LED Lamps (12V) | | | | | | | | | | | |
|------------------------------|----------------------------------|----------------------------------|----------------------------------|---------------|-----------------------|------------------|----------------|-----------------------|---|---|--|
| Manufacturer | Model | Transformer | Power | Compatibility | Number of CFL Lamps * | Dimming curve ** | Dimming mode** | Low dimming limit *** | High dimming limit*** | Observations | |
| G5.3 | VERBATIM | MR16 | Niko 320-00004 | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | Niko 320-00003 | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | Niko 320-00002 | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | MIMAVEN 150W | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | KRS LTD. 105 | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | Layrton TRI-50 ENC-C PTC | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | MCT 5402.0340.439 | 6W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | ELT TCE 5/23-E | 6W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | | ELT TCE 7/23-E | 6W | No | | | | | | Blinks during the dimming. |
| | | | OSRAM ET-ZE 60/220-240 | 6W | No | | | | | | Does not turn on. |
| | | | ThreeLine TT60 | 6W | No | | | | | | Blinks during the dimming. |
| | | | Niko 320-00101 | 6W | Yes | 1 | LED 1 or LED 2 | Trail | 20% | 100% | |
| | | | OSRAM HALOTRONIC HTL 225/230-240 | 6W | No | | | | | | Flash on the beginning of the dimming and there is not luminosity variation. |
| | | | OSRAM HALOTRONIC HTL 150/230-240 | 6W | No | | | | | | It is not possible to relative dimming. |
| | | | OSRAM HALOTRONIC HTL 70/230-240 | 6W | No | 1 | LED 1 or LED 2 | Lead | 1% | 100% | |
| | | | OSRAM HALOTRONIC HTL 105 230-240 | 6W | Yes | 1 | LED 2 | Lead | 1% | 100% | |
| | | | PHILIPS Primaline 105 230-240 | 6W | No | | | | | | It is not possible to relative dimming. |
| | PHILIPS Primaline 70 230-240 | 6W | No | | | | | | It is not possible to relative dimming. | | |
| | OSRAM | PARATHOM MR16 20 36º ADVANCED | Niko 320-00004 | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. |
| | | | Niko 320-00003 | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. |
| | | | Niko 320-00002 | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. |
| | | | MIMAVEN 150W | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer and blink during the dimming. |
| | | | KRS LTD. 105 | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. |
| | | | Layrton TRI-50 ENC-C PTC | 5W | Yes | 1-5 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. |
| | | | MCT 5402.0340.439 | 5W | No | | | | | | It is not possible to dim correctly. |
| | | | ELT TCE 5/23-E | 5W | Yes | 1-5 | LED 1 or LED 2 | Trail | 1% | 100% | |
| | | | ELT TCE 7/23-E | 5W | Yes | 1-5 | LED 1 or LED 2 | Trail | 5% | 100% | |
| | | | OSRAM ET-ZE 60/220-240 | 5W | No | | | | | | After an operating time, stops dimming. |
| | | ThreeLine TT60 | 5W | No | | | | | | It is not possible to dim correctly. | |
| | | Niko 320-00101 | 5W | Yes | 1-3 | LED 1 or LED 2 | Trail | 30% | 100% | | |
| | | | 5W | Yes | 4-5 | LED 1 or LED 2 | Trail | 3% | 100% | | |
| | | OSRAM HALOTRONIC HTL 225/230-240 | 5W | Yes | 1-4 | LED 1 or LED 2 | Trail | 1% | 100% | Dimming less than 5 lamps per channel, the luminosity is lower than normal operation. | |
| | | | 5W | Yes | 5 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | OSRAM HALOTRONIC HTL 150/230-240 | 5W | Yes | 1-5 | LED 2 | Trail | 1% | 100% | Blinks in the start of the dimming. | |
| | | OSRAM HALOTRONIC HTL 70/230-240 | 5W | Yes | 1-5 | LED 2 | Trail | 1% | 100% | Blinks in the start of the dimming. | |
| | | OSRAM HALOTRONIC HTL 105 230-240 | 5W | Yes | 1-5 | LED 2 | Trail | 1% | 100% | Blinks in the start of the dimming. | |
| | | PHILIPS Primaline 105 230-240 | 5W | Yes | 1-5 | LED 2 | Trail | 2% | 100% | Blinks in the start of the dimming. | |
| PHILIPS Primaline 70 230-240 | | 5W | Yes | 3-5 | LED 2 | Trail | 2% | 100% | Blinks in the start of the dimming. There is no possibility of dimming less than 3 lamps per channel. | | |
| OSRAM | PARATHOM MR16 60 ADVANCED | Niko 320-00004 | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | Niko 320-00003 | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | Niko 320-00002 | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | MIMAVEN 150W | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | KRS LTD. 105 | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | Layrton TRI-50 ENC-C PTC | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | MCT 5402.0340.439 | 11W | No | | | | | | It is not possible to dim correctly. | |
| | | ELT TCE 5/23-E | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | ELT TCE 7/23-E | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | OSRAM ET-ZE 60/220-240 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | 11W | Yes | 2 | LED 1 or LED 2 | Lead | 1% | 35% | | | |
| | ThreeLine TT60 | 11W | Yes | 3 | LED 1 or LED 2 | Lead | 1% | 100% | | | |
| | Niko 320-00101 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | | |
| | | 11W | Yes | 2 | LED 2 | Trail | 57% | 100% | | | |
| | OSRAM HALOTRONIC HTL 225/230-240 | 11W | Yes | 3 | LED 2 | Trail | 16% | 100% | | | |
| | OSRAM HALOTRONIC HTL 150/230-240 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 2% | 100% | | | |
| | OSRAM HALOTRONIC HTL 70/230-240 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | | |
| | OSRAM HALOTRONIC HTL 105 230-240 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | | |
| | PHILIPS Primaline 105 230-240 | 11W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | | |
| | PHILIPS Primaline 70 230-240 | 11W | Yes | 1-3 | LED 2 | Trail | 1% | 100% | | | |

| LED Lamps (12V) | | | | | | | | | | | | |
|----------------------------------|----------|------------------------|----------------------------------|---------------|-----------------------|------------------|------------------------|-------------------------------------|-----------------------|----------------|-------------------------------------|--------------------------------------|
| Manufacturer | Model | Transformer | Power | Compatibility | Number of CFL Lamps * | Dimming curve ** | Dimming mode** | Low dimming limit *** | High dimming limit*** | Observations | | |
| G5.3 | PHILIPS | MASTER LEDSPOT MR16 LV | Niko 320-00004 | 7W | Yes | 1-2 | Lineal | Lead | 20% | 100% | Blinks on the start of the dimming. | |
| | | | Niko 320-00003 | 7W | Yes | 1 | Lineal | Lead | 45% | 100% | Blinks on the start of the dimming. | |
| | | | Niko 320-00002 | 7W | Yes | 2 | Lineal | Lead | 20% | 100% | Blinks on the start of the dimming. | |
| | | | Niko 320-00002 | 7W | Yes | 1-2 | Lineal | Lead | 25% | 100% | Blinks on the start of the dimming. | |
| | | | MIMAVEN 150W | 7W | Yes | 1-2 | Lineal | Lead | 25% | 100% | Blinks on the start of the dimming. | |
| | | | KRS LTD. 105 | 7W | Yes | 1-2 | Lineal | Lead | 25% | 100% | Blinks on the start of the dimming. | |
| | | | Layrton TRI-50 ENC-C PTC | 7W | Yes | 1-2 | Lineal | Lead | 20% | 100% | Blinks on the start of the dimming. | |
| | | | MCT 5402.0340.439 | 7W | Yes | 1-2 | Lineal | Lead | 30% | 100% | Blinks on the start of the dimming. | |
| | | | ELT TCE 5/23-E | 7W | Yes | 1 | Lineal | Trail | 23% | 97% | Blinks on the start of the dimming. | |
| | | | ELT TCE 7/23-E | 7W | Yes | 2 | Lineal | Trail | 27% | 100% | Blinks on the start of the dimming. | |
| | | | ELT TCE 7/23-E | 7W | Yes | 1-2 | Lineal | Trail | 23% | 100% | Blinks on the start of the dimming. | |
| | | | OSRAM ET-ZE 60/220-240 | 7W | Yes | 2 | Lineal | Trail | 20% | 100% | | |
| | | | ThreeLine TT60 | 7W | Yes | 2 | Lineal | Lead | 17% | 100% | Blinks on the start of the dimming. | |
| | | | Niko 320-00101 | 7W | Yes | 1 | Lineal | Trail | 25% | 100% | Blinks on the start of the dimming. | |
| | | | Niko 320-00101 | 7W | Yes | 2 | Lineal | Trail | 30% | 100% | Blinks on the start of the dimming. | |
| | | | OSRAM HALOTRONIC HTL 225/230-240 | 7W | No | | | | | | | It is not possible to dim correctly. |
| | | | OSRAM HALOTRONIC HTL 150/230-240 | 7W | No | | | | | | | It is not possible to dim correctly. |
| | | | OSRAM HALOTRONIC HTL 70/230-240 | 7W | Yes | 1 | Lineal | Lead | 30% | 100% | Blinks on the start of the dimming. | |
| | | | OSRAM HALOTRONIC HTL 70/230-240 | 7W | Yes | 2 | Lineal | Lead | 35% | 100% | Blinks on the start of the dimming. | |
| | | | OSRAM HALOTRONIC HTL 105 230-240 | 7W | Yes | 1-2 | Lineal | Lead | 36% | 100% | Blinks on the start of the dimming. | |
| OSRAM HALOTRONIC HTL 105 230-240 | 7W | Yes | 1 | LED 2 | Trail | 25% | 100% | Blinks on the start of the dimming. | | | | |
| PHILIPS Primaline 105 230-240 | 7W | Yes | 2 | LED 2 | Trail | 38% | 100% | Blinks on the start of the dimming. | | | | |
| PHILIPS Primaline 105 230-240 | 7W | Yes | 2 | LED 2 | Trail | 27% | 100% | Blinks on the start of the dimming. | | | | |
| G53 | VERBATIM | AR111 | Niko 320-00004 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | Niko 320-00003 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | Niko 320-00002 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | MIMAVEN 150W | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | KRS LTD. 105 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | Layrton TRI-50 ENC-C PTC | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | MCT 5402.0340.439 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | ELT TCE 5/23-E | 16W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | | ELT TCE 7/23-E | 16W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | | OSRAM ET-ZE 60/220-240 | 16W | Yes | 1 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | | ThreeLine TT60 | 16W | Yes | 1 | Lineal, LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | Niko 320-00101 | 16W | Yes | 1 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | OSRAM HALOTRONIC HTL 225/230-240 | 16W | Yes | 1 | LED 2 | Trail | 1% | 100% | | |
| | | | OSRAM HALOTRONIC HTL 150/230-240 | 16W | Yes | 1 | Lineal, LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | | OSRAM HALOTRONIC HTL 70/230-240 | 16W | Yes | 1 | LED 2 | Lead | 1% | 100% | | |
| | | | OSRAM HALOTRONIC HTL 70/230-240 | 16W | Yes | 1 | LED 2 | Lead | 1% | 100% | | |
| | | | OSRAM HALOTRONIC HTL 105 230-240 | 16W | Yes | 1 | LED 2 | Lead | 1% | 100% | | |
| | | | PHILIPS Primaline 105 230-240 | 16W | Yes | 1 | LED 2 | Lead | 6% | 93% | | |
| | | | PHILIPS Primaline 105 230-240 | 16W | Yes | 1 | LED 2 | Lead | 2% | 93% | | |
| | | | G53 | SYLVANIA | REFLED AR111 | Niko 320-00004 | 10W | Yes | 1-4 | LED 1 or LED 2 | Lead | 1% |
| Niko 320-00003 | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| Niko 320-00002 | 10W | Yes | | | | 1-4 | LED 2 | Lead | 1% | 100% | | |
| MIMAVEN 150W | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| KRS LTD. 105 | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| Layrton TRI-50 ENC-C PTC | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| MCT 5402.0340.439 | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Lead | 2% | 100% | | |
| ELT TCE 5/23-E | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| ELT TCE 7/23-E | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| OSRAM ET-ZE 60/220-240 | 10W | Yes | | | | 1-4 | LED 2 | Trail | 1% | 100% | | |
| ThreeLine TT60 | 10W | Yes | | | | 2-4 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| Niko 320-00101 | 10W | Yes | | | | 1-4 | LED 2 | Lead/Trail | 1% | 100% | | |
| OSRAM HALOTRONIC HTL 225/230-240 | 10W | Yes | | | | 3 | Lineal | Trail | 15% | 100% | | |
| OSRAM HALOTRONIC HTL 225/230-240 | 10W | Yes | | | | 4 | Lineal | Trail | 13% | 100% | | |
| OSRAM HALOTRONIC HTL 150/230-240 | 10W | Yes | | | | 2 | LED 2 | Trail | 5% | 100% | | |
| OSRAM HALOTRONIC HTL 150/230-240 | 10W | Yes | | | | 3-4 | LED 2 | Trail | 1% | 100% | | |
| OSRAM HALOTRONIC HTL 70/230-240 | 10W | Yes | | | | 1-4 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| OSRAM HALOTRONIC HTL 105 230-240 | 10W | Yes | | | | 1-4 | LED 2 | Trail | 1% | 100% | | |
| PHILIPS Primaline 105 230-240 | 10W | Yes | | | | 1 | LED 2 | Trail | 15% | 100% | | |
| PHILIPS Primaline 105 230-240 | 10W | Yes | | | | 2-4 | LED 2 | Trail | 1% | 100% | | |
| PHILIPS Primaline 70 230-240 | 10W | Yes | 1 | LED 2 | Trail | 18% | 100% | | | | | |
| PHILIPS Primaline 70 230-240 | 10W | Yes | 2-4 | LED 2 | Trail | 1% | 100% | | | | | |

| LED Lamps (12V) | | | | | | | | | | | |
|----------------------------------|---|----------------------------------|--------------------------|----------------|-----------------------|------------------|----------------|---|---|--|---|
| Manufacturer | Model | Transformer | Power | Compatibility | Number of CFL Lamps * | Dimming curve ** | Dimming mode** | Low dimming limit *** | High dimming limit*** | Observations | |
| OSRAM | PARATHOM PRO LEDSPOT111 50 24º ADVANCED | Niko 320-00004 | 12W | Yes | 1-3 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | Niko 320-00003 | 12W | Yes | 1-3 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | Niko 320-00002 | 12W | Yes | 1-3 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | MIMAVEN 150W | 12W | Yes | 1-3 | LED 1 or LED 2 | Lead | 1% | 100% | | |
| | | KRS LTD. 105 | 12W | Yes | 1-3 | LED 1 or LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | Layrton TRI-50 ENC-C PTC | 12W | Yes | 1-3 | LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | MCT 5402.0340.439 | 12W | Yes | 1-3 | LED 2 | Lead | 1% | 100% | Noise in the transformer. | |
| | | ELT TCE 5/23-E | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | ELT TCE 7/23-E | 12W | Yes | 2-3 | LED 2 | Trail | 1% | 100% | It is not possible to dim less than 2 lamps per channel. | |
| | | OSRAM ET-ZE 60/220-240 | 12W | Yes | 1-3 | LED 2 | Trail | 1% | 100% | | |
| | | ThreeLine TT60 | 12W | Yes | 1 | LED 2 | Trail | 16% | 89% | | |
| | | | 12W | Yes | 2-3 | LED 2 | Trail | 1% | 100% | | |
| | | Niko 320-00101 | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | OSRAM HALOTRONIC HTL 225/230-240 | 12W | Yes | 2 | LED 2 | Trail | 1% | 100% | | |
| | | | 12W | Yes | 3 | LED 2 | Trail | 10% | 100% | | |
| | | OSRAM HALOTRONIC HTL 150/230-240 | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 2% | 100% | | |
| | | OSRAM HALOTRONIC HTL 70/230-240 | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | OSRAM HALOTRONIC HTL 105 230-240 | 12W | Yes | 1-3 | LED 1 or LED 2 | Trail | 1% | 100% | | |
| | | PHILIPS Primaline 105 230-240 | 12W | Yes | 2-3 | LED 1 or LED 2 | Trail | 1% | 100% | It is not possible to dim less than 2 lamps per channel. | |
| | | | 12W | Yes | 1 | LED 1 or LED 2 | Trail | 2% | 100% | | |
| | 12W | Yes | 2-3 | LED 1 or LED 2 | Trail | 1% | 100% | | | | |
| G.53 | PHILIPS | MASTER LEDSPOT AR111 LV | Niko 320-00004 | 15W | Yes | 1 | Lineal | Lead | 2% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 2-3 | Lineal | Lead | 25% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 1 | Lineal | Lead | 1% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | Niko 320-00003 | 15W | Yes | 2-3 | Lineal | Lead | 30% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 1 | Lineal | Lead | 20% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 2-3 | Lineal | Lead | 35% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | MIMAVEN 150W | 15W | Yes | 1 | Lineal | Lead | 25% | 100% | |
| | | | | 15W | Yes | 2-3 | Lineal | Lead | 20% | 100% | |
| | | | KRS LTD. 105 | 15W | Yes | 1-2 | Lineal | Lead | 20% | 85% | Noise in the transformer. |
| | | | | 15W | Yes | 3 | Lineal | Lead | 25% | 85% | Noise in the transformer. |
| | | | Layrton TRI-50 ENC-C PTC | 15W | Yes | 1-2 | Lineal | Lead | 25% | 100% | |
| | | | | 15W | Yes | 3 | Lineal | Lead | 31% | 100% | |
| | | | MCT 5402.0340.439 | 15W | Yes | 1-3 | Lineal | Lead | 20% | 100% | Noise in the transformer. |
| | | | ELT TCE 5/23-E | 15W | Yes | 1 | Lineal | Trail | 20% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 2-3 | Lineal | Trail | 30% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | ELT TCE 7/23-E | 15W | Yes | 1 | Lineal | Trail | 25% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 2-3 | Lineal | Trail | 35% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | OSRAM ET-ZE 60/220-240 | 15W | Yes | 1 | Lineal | Trail | 30% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | | 15W | Yes | 2-3 | Lineal | Trail | 35% | 100% | There is a little oscilation in the beginning of the dimming. |
| | | | ThreeLine TT60 | 15W | Yes | 1-3 | Lineal | Lead | 30% | 100% | There is a little oscilation in the beginning of the dimming. |
| Niko 320-00101 | 15W | Yes | 1-2 | Lineal | Lead | 30% | 100% | There is a little oscilation in the beginning of the dimming. | | | |
| | 15W | Yes | 3 | Lineal | Lead | 45% | 100% | There is a little oscilation in the beginning of the dimming. | | | |
| OSRAM HALOTRONIC HTL 225/230-240 | 15W | No | | | | | | | It is not possible to dim correctly. | | |
| OSRAM HALOTRONIC HTL 150/230-240 | 15W | No | | | | | | | It is not possible to dim correctly. | | |
| OSRAM HALOTRONIC HTL 70/230-240 | 15W | Yes | 1-3 | Lineal | Trail | 30% | 100% | There is a little oscilation in the beginning of the dimming. | | | |
| OSRAM HALOTRONIC HTL 105 230-240 | 15W | Yes | 1-2 | Lineal | Lead | 35% | 100% | There is a little oscilation in the beginning of the dimming. | | | |
| | 15W | Yes | 3 | Lineal | Lead | 25% | 100% | There is a little oscilation in the beginning of the dimming. | | | |
| PHILIPS Primaline 105 230-240 | 15W | No | | | | | | | It is not possible to dim correctly. | | |
| PHILIPS Primaline 70 230-240 | 15W | Yes | 3 | Lineal | Lead | 35% | 90% | | There is a little oscilation in the beginning of the dimming. It isn't possible to dim less than 3 lamps per channel. | | |

* This information is based in the test with DIMinBOX DX2 1.0 and a specific number of lamps of each type. It could control a higher number of lamps but it is ALWAYS necessary to test that number of lamps.

** The dimming curve and mode to configure in ETS parameters is based in the tests with the indicated number of lamps. It is necessary to test the number of lamps that will be installed with DIMinBOX DX2.

*** Some lamps flicker in low dimming levels or are only dimmable from a specific level, so it is necessary to set a Low Dimming Limit. And also, some lamps flicker in high dimming levels, because of that, it is necessary to set a High Dimming Limit.